

## 特點

- The TAB series remote display mounted in housing 72(w)×36(h)/ 96(w)×48(h)/ 144(w)×48(h), 4-digit or 5-digit or 6-digit or 8-digit.
- Data on BCD parallel 4 lines per digit (16 codes).
- Digit strobe on single lines or Binary multi-line.
- Display Code 0 ~ 9 & A, b, c, E, F ; or -, E, H, L, P, Blank.
- Decimal position setting by DIP SW. or remote input.
- Sever display can be linked together.



## 1. 選購型號 : MT-B - -

NO	外型尺寸	NO	顯示位數	NO	警報輸出	NO	工作電源	狀態選擇
3	72×36mm Case	3	3 digits (-199~999)	0	No Alarm Output	0	DC7~30V Power Supply	N : NPN P : PNP D : 動態 S : 靜態
9	96×48mm Case	4	4 digits (-1999~9999)	2	2 Alarm Outputs			
14	114×48mm Case	5	5 digits (-19999~99999)	4	4 Alarm Outputs			
		6	6 digits (-199999~999999)					
		8	8 digits (-19999999~99999999)					

## 2. 主要規格

- 輸入信號 : BCD Data Parallel or Multiplex Sinking or Sourcing Inputs
- 工作電源 : DC7~30V
- 消耗功率 : 3.5VA
- 輸入電流 : 10mA (max.) / each input line
- 顯示內容 : 0 ~ 9 ; A ~ F ; -, E, H, L, P, Blank
- 顯示字幕 :
  - MT-B3 Series**  
3-digit 0.8"(20mm) red LED  
4, 5-digit 0.56"(14.2mm) red LED  
6-digit 0.4"(10mm) red LED  
8-digit 0.3"(7.6mm) red LED
  - MT-B9 Series**  
4-digit 0.8"(20mm) red LED  
6-digit 0.56"(14.2mm) red LED  
8-digit 0.4"(10mm) red LED
  - MT-B14 Series**  
5-digit 1.0"(25.4mm) red LED  
6-digit 0.8"(20mm) red LED  
8-digit 0.56"(14.2mm) red LED
- 小數設定 : Setting by DIP SW or form control input line
- 使用環境條件 : 0~50°C (45 to 85% RH)
- 外型尺寸 : MT-B3 Series 72(W)×36(H)×117(D)mm  
MT-B9 Series 96(W)×48(H)×98(D)mm  
MT-B14 Series 144(W)×48(H)×98(D)mm
- 開孔尺寸 : MT-B3 Series 68(W)×33(H)mm  
MT-B9 Series 92(W)×44(H)mm  
MT-B14 Series 140(W)×44(H)mm

## 3. 外型與開孔尺寸圖

