

特點

- 精確度 0.05% 滿刻度 ±1 位數
- 可量測交直流電流/交直流電壓/電位計/傳送器/Pt-100/荷重元/電阻 等信號
- 顯示範圍 -19999 ~ 99999 可任意規劃
- 2 組警報功能
- 具有自動歸零與保持功能
- 尺寸小, 穩定性高
- 操作簡易(指撥開關設定)



1. 選購型號 : MA-SXAP - - => X=4(4 digit setting, -9999~+9999), X=5(5 digit setting, 0~99999)

NO	Input Type	NO	DCV (ACV)	NO	DCA(ACA)	NO	Potentiometer	NO	Transmitter	NO	Pt-100	NO	Load Cell	NO	Alarm output	NO	Aux. Power
A	DC	11	0-50mV	21	0-9.9999uA	31	0-10%	41	DC4-20mA	51	-50.00 ~ +50.00	61	2mV/V	1	One	A	AC110/220V
B	AC(RMS)	12	0-5V	22	0-99.999uA	32	0-50%	42	DC1-5V	52	-100.00 ~ +100.00	62	3mV/V	2	Two	B	AC/DC20~60V
C	AC (TRMS)	13	0-10V	23	0-999.99uA	33	0-100%	43	DC4-20mA	53	-200.0 ~ +400.0	63	2mV/V	Relay contact (AC250V-5A, DC30V-7A)	C	AC/DC90~260V	Less 4VA for AC/DC input (50/60Hz)
D	Potentiometer	14	0-36V	24	0-9.9999mA	34	5-95%	44	DC1-5V	54	-200.0 ~ +850.0	64	3mV/V				
E	Transmitter	15	0-54V	25	0-99.999mA	35	10-90%	49	SPECIFIED	59	SPECIFIED	69	SPECIFIED				
F	Pt-100(RTD)	16	0-110V	26	0-999.99mA	39	SPECIFIED	Three wire connection		Three wire connection		Three wire connection					
H	Load Cell	17	0-600V	27	0-5.000A	Three wire connection Exciting voltg DC2.5V(<10mA)		41/42 nonexciting DC24V 43/44 exciting DC24V(<25mA)		Three wire connection		61/62 Exciting DC5V(<100mA) 63/64 Exciting DC10V(<50mA)					
L	LVDT	18	0-1000V	28	0-9.9999A	Three wire connection Exciting voltg DC2.5V(<10mA)		41/42 nonexciting DC24V 43/44 exciting DC24V(<25mA)		Three wire connection		61/62 Exciting DC5V(<100mA) 63/64 Exciting DC10V(<50mA)					
R	Resistor	19	SPECIFIED	29	SPECIFIED	Three wire connection Exciting voltg DC2.5V(<10mA)		41/42 nonexciting DC24V 43/44 exciting DC24V(<25mA)		Three wire connection		61/62 Exciting DC5V(<100mA) 63/64 Exciting DC10V(<50mA)					
O	SPECIFIED					Three wire connection Exciting voltg DC2.5V(<10mA)		41/42 nonexciting DC24V 43/44 exciting DC24V(<25mA)		Three wire connection		61/62 Exciting DC5V(<100mA) 63/64 Exciting DC10V(<50mA)					

2. 主要規格

- 精確度(23 ± 5) : 0.05% F.S. ± 1digit
0.2% F.S. ± 1digit (AC(RMS))
- 取樣時間 : 16 cycles/sec.
- 顯示值範圍 : -19999 ~ 99999 digit adjustable
- 設定值範圍 : -9999 ~ +9999 digit adjustable (4 digit setting)
0 ~ 99999 digit adjustable (5 digit setting)
- 比較值設定方式 : Pushwheel digital switches
- 繼電器動作方向 : HI or Lo adjustable
- 比較不感帶 : 0 ~ 999 digit adjustable
- 繼電器延遲動作時間 : 0 ~ 99.9 second adjustable
- 繼電器容量 : AC 250-5A, DC30V-7A
- 溫度係數 : 50ppm/ (0-50)
- 顯示幕 : Red high efficiency LEDs high 10.16mm(0.4")
- 參數設定方式 : Touch switches
- 記憶型式 : Non-volatile E² PROM memory
- 絕緣耐壓能力 : 2KVac/1 min. (input/output/power)
1600 Vdc (input/output)
- 使用環境條件 : 0~50 (20 to 90% RH non-condensed)
- 存放環境條件 : 0~70 (20 to 90% RH non-condensed)

3. 外型/開孔尺寸與配線圖

